

## Enclosed Alphanumeric Supplement

Range: 1F100–1F1FF

### The Unicode Standard, Version 14.0

This file contains an excerpt from the character code tables and list of character names for *The Unicode Standard, Version 14.0*

Characters in this chart that are new for The Unicode Standard, Version 14.0 are shown in conjunction with any existing characters. For ease of reference, the new characters have been highlighted in the chart grid and in the names list.

This file will not be updated with errata, or when additional characters are assigned to the Unicode Standard. See <https://www.unicode.org/errata/> for an up-to-date list of errata.

See <https://www.unicode.org/charts/> for access to a complete list of the latest character code charts. See <https://www.unicode.org/charts/PDF/Unicode-14.0/> for charts showing only the characters added in Unicode 14.0. See <https://www.unicode.org/Public/14.0.0/charts/> for a complete archived file of character code charts for Unicode 14.0.

### Disclaimer

These charts are provided as the online reference to the character contents of the Unicode Standard, Version 14.0 but do not provide all the information needed to fully support individual scripts using the Unicode Standard. For a complete understanding of the use of the characters contained in this file, please consult the appropriate sections of The Unicode Standard, Version 14.0, online at <https://www.unicode.org/versions/Unicode14.0.0/>, as well as Unicode Standard Annexes #9, #11, #14, #15, #24, #29, #31, #34, #38, #41, #42, #44, #45, and #50, the other Unicode Technical Reports and Standards, and the Unicode Character Database, which are available online.

See <https://www.unicode.org/ucd/> and <https://www.unicode.org/reports/>

A thorough understanding of the information contained in these additional sources is required for a successful implementation.

Copying characters from the character code tables or list of character names is not recommended, because for production reasons the PDF files for the code charts cannot guarantee that the correct character codes will always be copied.

### Fonts

The shapes of the reference glyphs used in these code charts are not prescriptive. Considerable variation is to be expected in actual fonts. The particular fonts used in these charts were provided to the Unicode Consortium by a number of different font designers, who own the rights to the fonts.

See <https://www.unicode.org/charts/fonts.html> for a list.

### Terms of Use

You may freely use these code charts for personal or internal business uses only. You may not incorporate them either wholly or in part into any product or publication, or otherwise distribute them without express written permission from the Unicode Consortium. However, you may provide links to these charts.

The fonts and font data used in production of these code charts may NOT be extracted, or used in any other way in any product or publication, without permission or license granted by the typeface owner(s).

The Unicode Consortium is not liable for errors or omissions in this file or the standard itself. Information on characters added to the Unicode Standard since the publication of the most recent version of the Unicode Standard, as well as on characters currently being considered for addition to the Unicode Standard can be found on the Unicode web site.

See <https://www.unicode.org/pending/pending.html> and <https://www.unicode.org/alloc/Pipeline.html>.

Copyright © 1991-2021 Unicode, Inc. All rights reserved.

	1F10	1F11	1F12	1F13	1F14	1F15	1F16	1F17	1F18	1F19	1F1A	1F1B	1F1C	1F1D	1F1E	1F1F
0	0. (1F100)	(A) (1F110)	(Q) (1F120)	A (1F130)	Q (1F140)	A (1F150)	Q (1F160)	A (1F170)	Q (1F180)	DJ (1F190)	5.1 (1F1A0)					K (1F1F0)
1	0, (1F101)	(B) (1F111)	(R) (1F121)	B (1F131)	R (1F141)	B (1F151)	R (1F161)	B (1F171)	R (1F181)	CL (1F191)	7.1 (1F1A1)					L (1F1F1)
2	1, (1F102)	(C) (1F112)	(S) (1F122)	C (1F132)	S (1F142)	C (1F152)	S (1F162)	C (1F172)	S (1F182)	COOL (1F192)	22.2 (1F1A2)					M (1F1F2)
3	2, (1F103)	(D) (1F113)	(T) (1F123)	D (1F133)	T (1F143)	D (1F153)	T (1F163)	D (1F173)	T (1F183)	FREE (1F193)	60P (1F1A3)					N (1F1F3)
4	3, (1F104)	(E) (1F114)	(U) (1F124)	E (1F134)	U (1F144)	E (1F154)	U (1F164)	E (1F174)	U (1F184)	ID (1F194)	120P (1F1A4)					O (1F1F4)
5	4, (1F105)	(F) (1F115)	(V) (1F125)	F (1F135)	V (1F145)	F (1F155)	V (1F165)	F (1F175)	V (1F185)	NEW (1F195)	d (1F1A5)					P (1F1F5)
6	5, (1F106)	(G) (1F116)	(W) (1F126)	G (1F136)	W (1F146)	G (1F156)	W (1F166)	G (1F176)	W (1F186)	NG (1F196)	HC (1F1A6)				A (1F1E6)	Q (1F1F6)
7	6, (1F107)	(H) (1F117)	(X) (1F127)	H (1F137)	X (1F147)	H (1F157)	X (1F167)	H (1F177)	X (1F187)	OK (1F197)	HDR (1F1A7)				B (1F1E7)	R (1F1F7)
8	7, (1F108)	(I) (1F118)	(Y) (1F128)	I (1F138)	Y (1F148)	I (1F158)	Y (1F168)	I (1F178)	Y (1F188)	SOS (1F198)	Hi-Res (1F1A8)				C (1F1E8)	S (1F1F8)
9	8, (1F109)	(J) (1F119)	(Z) (1F129)	J (1F139)	Z (1F149)	J (1F159)	Z (1F169)	J (1F179)	Z (1F189)	UP! (1F199)	Loss less (1F1A9)				D (1F1E9)	T (1F1F9)
A	9, (1F10A)	(K) (1F11A)	(S) (1F12A)	K (1F13A)	HV (1F14A)	K (1F15A)	MC (1F16A)	K (1F17A)	P (1F18A)	VS (1F19A)	SHV (1F1AA)				E (1F1EA)	U (1F1FA)
B	0 (1F10B)	(L) (1F11B)	(C) (1F12B)	L (1F13B)	MV (1F14B)	L (1F15B)	MD (1F16B)	L (1F17B)	IC (1F18B)	3D (1F19B)	UHD (1F1AB)				F (1F1EB)	V (1F1FB)
C	0 (1F10C)	(M) (1F11C)	(R) (1F12C)	M (1F13C)	SD (1F14C)	M (1F15C)	MR (1F16C)	M (1F17C)	PA (1F18C)	2nd Scr (1F19C)	VOD (1F1AC)				G (1F1EC)	W (1F1FC)
D	0 (1F10D)	(N) (1F11D)	(CD) (1F12D)	N (1F13D)	SS (1F14D)	N (1F15D)	CC (1F16D)	N (1F17D)	SA (1F18D)	2K (1F19D)	M (1F1AD)				H (1F1ED)	X (1F1FD)
E	0 (1F10E)	(O) (1F11E)	(Wz) (1F12E)	O (1F13E)	PPV (1F14E)	O (1F15E)	0 (1F16E)	O (1F17E)	AB (1F18E)	4K (1F19E)					I (1F1EE)	Y (1F1FE)
F	0 (1F10F)	(P) (1F11F)	0 (1F12F)	P (1F13F)	WC (1F14F)	P (1F15F)	i (1F16F)	P (1F17F)	WC (1F18F)	8K (1F19F)					J (1F1EF)	Z (1F1FF)

**Number with full stop**

This symbol completes the set of numbers with full stop starting at 2488.

1F100 0. DIGIT ZERO FULL STOP  
≈ 0030 0 002E .

**Numbers with comma**

1F101 0, DIGIT ZERO COMMA  
≈ 0030 0 002C ,

1F102 1, DIGIT ONE COMMA  
≈ 0031 1 002C ,

1F103 2, DIGIT TWO COMMA  
≈ 0032 2 002C ,

1F104 3, DIGIT THREE COMMA  
≈ 0033 3 002C ,

1F105 4, DIGIT FOUR COMMA  
≈ 0034 4 002C ,

1F106 5, DIGIT FIVE COMMA  
≈ 0035 5 002C ,

1F107 6, DIGIT SIX COMMA  
≈ 0036 6 002C ,

1F108 7, DIGIT SEVEN COMMA  
≈ 0037 7 002C ,

1F109 8, DIGIT EIGHT COMMA  
≈ 0038 8 002C ,

1F10A 9, DIGIT NINE COMMA  
≈ 0039 9 002C ,

**Circled sans-serif digits**

These digits complement the sans-serif digit sets in the Dingbat block ranges 2780-2789 and 278A-2793.

1F10B ① DINGBAT CIRCLED SANS-SERIF DIGIT ZERO

1F10C ⓪ DINGBAT NEGATIVE CIRCLED SANS-SERIF DIGIT ZERO

**Creative Commons symbols**

Part of a Creative Commons symbol set also including 229C, 1F16D, 1F16E, and 1F16F.

1F10D ⓪ CIRCLED ZERO WITH SLASH  
= no rights reserved

1F10E Ⓜ CIRCLED ANTICLOCKWISE ARROW  
= share alike

1F10F Ⓢ CIRCLED DOLLAR SIGN WITH OVERLAID BACKSLASH  
= non commercial

**Parenthesized Latin letters**

This set provides uppercase versions of the set starting at 249C. Parenthesized Latin letters do not have case mappings.

1F110 (A) PARENTHESIZED LATIN CAPITAL LETTER A  
≈ 0028 ( 0041 A 0029 )

1F111 (B) PARENTHESIZED LATIN CAPITAL LETTER B  
≈ 0028 ( 0042 B 0029 )

1F112 (C) PARENTHESIZED LATIN CAPITAL LETTER C  
≈ 0028 ( 0043 C 0029 )

1F113 (D) PARENTHESIZED LATIN CAPITAL LETTER D  
≈ 0028 ( 0044 D 0029 )

1F114 (E) PARENTHESIZED LATIN CAPITAL LETTER E  
≈ 0028 ( 0045 E 0029 )

1F115 (F) PARENTHESIZED LATIN CAPITAL LETTER F  
≈ 0028 ( 0046 F 0029 )

1F116 (G) PARENTHESIZED LATIN CAPITAL LETTER G  
≈ 0028 ( 0047 G 0029 )

1F117 (H) PARENTHESIZED LATIN CAPITAL LETTER H  
≈ 0028 ( 0048 H 0029 )

1F118 (I) PARENTHESIZED LATIN CAPITAL LETTER I  
≈ 0028 ( 0049 I 0029 )

1F119 (J) PARENTHESIZED LATIN CAPITAL LETTER J  
≈ 0028 ( 004A J 0029 )

1F11A (K) PARENTHESIZED LATIN CAPITAL LETTER K  
≈ 0028 ( 004B K 0029 )

1F11B (L) PARENTHESIZED LATIN CAPITAL LETTER L  
≈ 0028 ( 004C L 0029 )

1F11C (M) PARENTHESIZED LATIN CAPITAL LETTER M  
≈ 0028 ( 004D M 0029 )

1F11D (N) PARENTHESIZED LATIN CAPITAL LETTER N  
≈ 0028 ( 004E N 0029 )

1F11E (O) PARENTHESIZED LATIN CAPITAL LETTER O  
≈ 0028 ( 004F O 0029 )

1F11F (P) PARENTHESIZED LATIN CAPITAL LETTER P  
≈ 0028 ( 0050 P 0029 )

1F120 (Q) PARENTHESIZED LATIN CAPITAL LETTER Q  
≈ 0028 ( 0051 Q 0029 )

1F121 (R) PARENTHESIZED LATIN CAPITAL LETTER R  
≈ 0028 ( 0052 R 0029 )

1F122 (S) PARENTHESIZED LATIN CAPITAL LETTER S  
≈ 0028 ( 0053 S 0029 )

1F123 (T) PARENTHESIZED LATIN CAPITAL LETTER T  
≈ 0028 ( 0054 T 0029 )

1F124 (U) PARENTHESIZED LATIN CAPITAL LETTER U  
≈ 0028 ( 0055 U 0029 )

1F125 (V) PARENTHESIZED LATIN CAPITAL LETTER V  
≈ 0028 ( 0056 V 0029 )

1F126 (W) PARENTHESIZED LATIN CAPITAL LETTER W  
≈ 0028 ( 0057 W 0029 )

1F127 (X) PARENTHESIZED LATIN CAPITAL LETTER X  
≈ 0028 ( 0058 X 0029 )

1F128 (Y) PARENTHESIZED LATIN CAPITAL LETTER Y  
≈ 0028 ( 0059 Y 0029 )

1F129 (Z) PARENTHESIZED LATIN CAPITAL LETTER Z  
≈ 0028 ( 005A Z 0029 )

**Latin letter with tortoise shell brackets**

1F12A [S] TORTOISE SHELL BRACKETED LATIN CAPITAL LETTER S  
• used in baseball scoring  
≈ 3014 [ 0053 S 3015 ]

**Circled italic Latin letters**

1F12B © CIRCLED ITALIC LATIN CAPITAL LETTER C  
= compact disc, single disc record  
≈ <circle> 0043 C

1F12C ® CIRCLED ITALIC LATIN CAPITAL LETTER R  
= disc record  
≈ <circle> 0052 R

**Circled Latin letters or letter sequences**

1F12D Ⓒ CIRCLED CD  
→ 33C5 cd square cd  
≈ <circle> 0043 C 0044 D

1F12E ™ CIRCLED WZ  
• from the German term "Warenzeichen"  
• indicate a trademarked term without making a legal claim of trademark status  
• decomposition is anomalous, as the usual glyph shows a capital W and a small z  
→ 2122 ™ trade mark sign  
≈ <circle> 0057 W 005A Z

1F12F ☉ COPYLEFT SYMBOL  
 → 00A9 ☉ copyright sign  
 → 2183 ㊀ roman numeral reversed one hundred

**Squared Latin letters**

1F130 [A] SQUARED LATIN CAPITAL LETTER A  
 = Anreisetag (day of arrival)  
 ≈ <square> 0041 A

1F131 [B] SQUARED LATIN CAPITAL LETTER B  
 = bank  
 = b-mode stereo compression broadcasting service (ARIB STD B24)  
 ≈ <square> 0042 B

1F132 [C] SQUARED LATIN CAPITAL LETTER C  
 ≈ <square> 0043 C

1F133 [D] SQUARED LATIN CAPITAL LETTER D  
 ≈ <square> 0044 D

1F134 [E] SQUARED LATIN CAPITAL LETTER E  
 ≈ <square> 0045 E

1F135 [F] SQUARED LATIN CAPITAL LETTER F  
 ≈ <square> 0046 F

1F136 [G] SQUARED LATIN CAPITAL LETTER G  
 ≈ <square> 0047 G

1F137 [H] SQUARED LATIN CAPITAL LETTER H  
 ≈ <square> 0048 H

1F138 [I] SQUARED LATIN CAPITAL LETTER I  
 ≈ <square> 0049 I

1F139 [J] SQUARED LATIN CAPITAL LETTER J  
 ≈ <square> 004A J

1F13A [K] SQUARED LATIN CAPITAL LETTER K  
 ≈ <square> 004B K

1F13B [L] SQUARED LATIN CAPITAL LETTER L  
 ≈ <square> 004C L

1F13C [M] SQUARED LATIN CAPITAL LETTER M  
 ≈ <square> 004D M

1F13D [N] SQUARED LATIN CAPITAL LETTER N  
 = news (ARIB STD B24)  
 ≈ <square> 004E N

1F13E [O] SQUARED LATIN CAPITAL LETTER O  
 ≈ <square> 004F O

1F13F [P] SQUARED LATIN CAPITAL LETTER P  
 = progressive broadcasting (ARIB STD B24)  
 ≈ <square> 0050 P

1F140 [Q] SQUARED LATIN CAPITAL LETTER Q  
 ≈ <square> 0051 Q

1F141 [R] SQUARED LATIN CAPITAL LETTER R  
 ≈ <square> 0052 R

1F142 [S] SQUARED LATIN CAPITAL LETTER S  
 = stereo broadcasting service (ARIB STD B24)  
 ≈ <square> 0053 S

1F143 [T] SQUARED LATIN CAPITAL LETTER T  
 = tobacconist  
 ≈ <square> 0054 T

1F144 [U] SQUARED LATIN CAPITAL LETTER U  
 ≈ <square> 0055 U

1F145 [V] SQUARED LATIN CAPITAL LETTER V  
 ≈ <square> 0056 V

1F146 [W] SQUARED LATIN CAPITAL LETTER W  
 = wide-format 16:9 broadcasting service (ARIB STD B24)  
 ≈ <square> 0057 W

1F147 [X] SQUARED LATIN CAPITAL LETTER X  
 ≈ <square> 0058 X

1F148 [Y] SQUARED LATIN CAPITAL LETTER Y  
 ≈ <square> 0059 Y

1F149 [Z] SQUARED LATIN CAPITAL LETTER Z  
 ≈ <square> 005A Z

1F14A [HV] SQUARED HV  
 = hdtv  
 ≈ <square> 0048 H 0056 V

1F14B [MV] SQUARED MV  
 = multi-view television  
 ≈ <square> 004D M 0056 V

1F14C [SD] SQUARED SD  
 = sdtv  
 ≈ <square> 0053 S 0044 D

1F14D [SS] SQUARED SS  
 = surround stereo broadcasting service  
 ≈ <square> 0053 S 0053 S

1F14E [PPV] SQUARED PPV  
 = pay-per-view  
 ≈ <square> 0050 P 0050 P 0056 V

1F14F [WC] SQUARED WC  
 = water closet, public toilet  
 → 1F6BE 🚻 water closet  
 ≈ <square> 0057 W 0043 C

**White on black circled Latin letters**

1F150 [A] NEGATIVE CIRCLED LATIN CAPITAL LETTER A  
 = airport

1F151 [B] NEGATIVE CIRCLED LATIN CAPITAL LETTER B

1F152 [C] NEGATIVE CIRCLED LATIN CAPITAL LETTER C

1F153 [D] NEGATIVE CIRCLED LATIN CAPITAL LETTER D

1F154 [E] NEGATIVE CIRCLED LATIN CAPITAL LETTER E

1F155 [F] NEGATIVE CIRCLED LATIN CAPITAL LETTER F  
 = ferry

1F156 [G] NEGATIVE CIRCLED LATIN CAPITAL LETTER G

1F157 [H] NEGATIVE CIRCLED LATIN CAPITAL LETTER H  
 = hotel (ARIB STD B24)

1F158 [I] NEGATIVE CIRCLED LATIN CAPITAL LETTER I

1F159 [J] NEGATIVE CIRCLED LATIN CAPITAL LETTER J

1F15A [K] NEGATIVE CIRCLED LATIN CAPITAL LETTER K  
 = Kurort (spa)  
 → 2668 🌡️ hot springs

1F15B [L] NEGATIVE CIRCLED LATIN CAPITAL LETTER L  
 = light rail  
 → 1F688 🚆 light rail

1F15C [M] NEGATIVE CIRCLED LATIN CAPITAL LETTER M  
 = metro  
 → 1F687 🚇 metro

1F15D [N] NEGATIVE CIRCLED LATIN CAPITAL LETTER N

1F15E [O] NEGATIVE CIRCLED LATIN CAPITAL LETTER O

1F15F [P] NEGATIVE CIRCLED LATIN CAPITAL LETTER P  
 = parking space (ARIB STD B24)

1F160 [Q] NEGATIVE CIRCLED LATIN CAPITAL LETTER Q

1F161 [R] NEGATIVE CIRCLED LATIN CAPITAL LETTER R  
 = Raststätte (rest stop)

1F162 [S] NEGATIVE CIRCLED LATIN CAPITAL LETTER S  
 = Stadtbahn (metropolitan railway)

1F163 [T] NEGATIVE CIRCLED LATIN CAPITAL LETTER T  
 = Tankstelle (petrol station)  
 → 26FD 🛢️ fuel pump

1F164 [U] NEGATIVE CIRCLED LATIN CAPITAL LETTER U  
 = underground rail  
 → 1F687 🚇 metro

1F165 [V] NEGATIVE CIRCLED LATIN CAPITAL LETTER V

1F166 [W] NEGATIVE CIRCLED LATIN CAPITAL LETTER W

1F167	ⓧ	NEGATIVE CIRCLED LATIN CAPITAL LETTER X
1F168	Ⓨ	NEGATIVE CIRCLED LATIN CAPITAL LETTER Y
1F169	Ⓩ	NEGATIVE CIRCLED LATIN CAPITAL LETTER Z

**Raised squared Latin sequences**

1F16A	<sup>MC</sup>	<b>RAISED MC SIGN</b> = marque de commerce • used in Canada → 2122 ™ trade mark sign ≈ <sup> 004D <b>M</b> 0043 <b>C</b>
1F16B	<sup>MD</sup>	<b>RAISED MD SIGN</b> = marque déposée • used in Canada → 00AE ® registered sign ≈ <sup> 004D <b>M</b> 0044 <b>D</b>
1F16C	<sup>MR</sup>	<b>RAISED MR SIGN</b> = marca registrada • used primarily in Spanish and Portuguese speaking communities to indicate a registered trademark → 00AE ® registered sign ≈ <sup> 004D <b>M</b> 0052 <b>R</b>

**Creative Commons symbols**

1F16D	©	<b>CIRCLED CC</b> = Creative Commons license → 229C Ⓔ circled equals
1F16E	∞	<b>CIRCLED C WITH OVERLAID BACKSLASH</b> = public domain
1F16F	👤	<b>CIRCLED HUMAN FIGURE</b> = attribution, credit

**White on black squared Latin letters**

*The square edges may be slightly rounded.*

1F170	Ⓐ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER A</b> = blood type A
1F171	Ⓑ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER B</b> = blood type B
1F172	Ⓒ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER C</b> = centre, city centre
1F173	Ⓓ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER D</b>
1F174	Ⓔ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER E</b>
1F175	Ⓕ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER F</b> = Feuerwache (fire department)
1F176	Ⓖ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER G</b>
1F177	Ⓗ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER H</b> = Haltestelle (bus stop) → 1F68F 🚏 bus stop
1F178	Ⓘ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER I</b>
1F179	Ⓙ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER J</b> = junction (ARIB STD B24)
1F17A	Ⓚ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER K</b>
1F17B	Ⓛ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER L</b> = leisure center (ARIB STD B24)
1F17C	Ⓜ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER M</b> = museum, cultural center (ARIB STD B24)
1F17D	Ⓝ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER N</b>
1F17E	Ⓞ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER O</b> = blood type O
1F17F	Ⓟ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER P</b> = parking space empty-full (ARIB STD B24)
1F180	Ⓠ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER Q</b>
1F181	Ⓡ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER R</b>
1F182	Ⓢ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER S</b>
1F183	Ⓣ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER T</b>

1F184	Ⓤ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER U</b>
1F185	Ⓥ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER V</b>
1F186	Ⓦ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER W</b>
1F187	Ⓧ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER X</b>
1F188	Ⓨ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER Y</b>
1F189	Ⓩ	<b>NEGATIVE SQUARED LATIN CAPITAL LETTER Z</b>
1F18A	Ⓟ	<b>CROSSED NEGATIVE SQUARED LATIN CAPITAL LETTER P</b> = parking space closed
1F18B	Ⓠ	<b>NEGATIVE SQUARED IC</b> = interchange, ramp
1F18C	Ⓡ	<b>NEGATIVE SQUARED PA</b> = parking area
1F18D	Ⓢ	<b>NEGATIVE SQUARED SA</b> = service area
1F18E	Ⓣ	<b>NEGATIVE SQUARED AB</b> = blood type AB
1F18F	Ⓦ	<b>NEGATIVE SQUARED WC</b> = water closet, public toilet → 1F6BE 🚻 water closet

**Squared Latin letter sequences**


1F190	Ⓓ	<b>SQUARE DJ</b> = disc jockey ≈ <square> 0044 <b>D</b> 004A <b>J</b>
1F191	Ⓒ	<b>SQUARED CL</b> = clear
1F192	Ⓒ	<b>SQUARED COOL</b>
1F193	Ⓒ	<b>SQUARED FREE</b> = free postage
1F194	Ⓓ	<b>SQUARED ID</b> = identification, ID
1F195	Ⓒ	<b>SQUARED NEW</b>
1F196	Ⓒ	<b>SQUARED NG</b> = no good
1F197	Ⓒ	<b>SQUARED OK</b>
1F198	Ⓒ	<b>SQUARED SOS</b> = search, hunt for missing person
1F199	Ⓒ	<b>SQUARED UP WITH EXCLAMATION MARK</b> = new information, update
1F19A	Ⓒ	<b>SQUARED VS</b> = versus

**Squared Latin letter sequences from ARIB STD B62**

1F19B	Ⓒ	<b>SQUARED THREE D</b>
1F19C	Ⓒ	<b>SQUARED SECOND SCREEN</b>
1F19D	Ⓒ	<b>SQUARED TWO K</b>
1F19E	Ⓒ	<b>SQUARED FOUR K</b>
1F19F	Ⓒ	<b>SQUARED EIGHT K</b>
1F1A0	Ⓒ	<b>SQUARED FIVE POINT ONE</b> • denotes 5.1-channel surround sound
1F1A1	Ⓒ	<b>SQUARED SEVEN POINT ONE</b> • denotes 7.1-channel surround sound
1F1A2	Ⓒ	<b>SQUARED TWENTY-TWO POINT TWO</b> • denotes 22.2-channel surround sound
1F1A3	Ⓒ	<b>SQUARED SIXTY P</b> • denotes 60Hz frame rate with progressive scanning
1F1A4	Ⓒ	<b>SQUARED ONE HUNDRED TWENTY P</b> • denotes 120Hz frame rate with progressive scanning
1F1A5	Ⓒ	<b>SQUARED LATIN SMALL LETTER D</b> = data
1F1A6	Ⓒ	<b>SQUARED HC</b> = hybrid cast



























1F1A7		SQUARED HDR = high dynamic range
1F1A8		SQUARED HI-RES = high resolution
1F1A9		SQUARED LOSSLESS
1F1AA		SQUARED SHV = super high vision
1F1AB		SQUARED UHD = ultra-high definition
1F1AC		SQUARED VOD = video on demand

**Miscellaneous symbol**

1F1AD		MASK WORK SYMBOL <ul style="list-style-type: none"> <li>• indicates intellectual property protection for integrated circuit layouts</li> <li>→ 00A9 © copyright sign</li> <li>→ 24C2 Ⓜ circled latin capital letter m</li> </ul>
-------	---	--

**Regional indicator symbols**

*These characters can be used in pairs to represent regional codes. In some emoji implementations, certain pairs may be recognized and displayed by alternate means; for instance, an implementation might recognize F + R and display this combination with a symbol representing the flag of France.*

1F1E6		REGIONAL INDICATOR SYMBOL LETTER A
1F1E7		REGIONAL INDICATOR SYMBOL LETTER B
1F1E8		REGIONAL INDICATOR SYMBOL LETTER C
1F1E9		REGIONAL INDICATOR SYMBOL LETTER D
1F1EA		REGIONAL INDICATOR SYMBOL LETTER E
1F1EB		REGIONAL INDICATOR SYMBOL LETTER F
1F1EC		REGIONAL INDICATOR SYMBOL LETTER G
1F1ED		REGIONAL INDICATOR SYMBOL LETTER H
1F1EE		REGIONAL INDICATOR SYMBOL LETTER I
1F1EF		REGIONAL INDICATOR SYMBOL LETTER J
1F1F0		REGIONAL INDICATOR SYMBOL LETTER K
1F1F1		REGIONAL INDICATOR SYMBOL LETTER L
1F1F2		REGIONAL INDICATOR SYMBOL LETTER M
1F1F3		REGIONAL INDICATOR SYMBOL LETTER N
1F1F4		REGIONAL INDICATOR SYMBOL LETTER O
1F1F5		REGIONAL INDICATOR SYMBOL LETTER P
1F1F6		REGIONAL INDICATOR SYMBOL LETTER Q
1F1F7		REGIONAL INDICATOR SYMBOL LETTER R
1F1F8		REGIONAL INDICATOR SYMBOL LETTER S
1F1F9		REGIONAL INDICATOR SYMBOL LETTER T
1F1FA		REGIONAL INDICATOR SYMBOL LETTER U
1F1FB		REGIONAL INDICATOR SYMBOL LETTER V
1F1FC		REGIONAL INDICATOR SYMBOL LETTER W
1F1FD		REGIONAL INDICATOR SYMBOL LETTER X
1F1FE		REGIONAL INDICATOR SYMBOL LETTER Y
1F1FF		REGIONAL INDICATOR SYMBOL LETTER Z